

Enerlites®

30-MINUTE 7-BUTTON COUNTDOWN TIMER SWITCH

MODEL NO: HET06A-R



DESCRIPTION

The ENERLITES HET06A-R is an in-wall timer switch with 7 buttons. The buttons offer 6 preset countdown times ranging from 1 minute to 30 minutes and one manual ON/OFF button that can override the timer. The timer switch features blue LED indicators that stay ON for easy locating in the dark. This device can work with incandescent, fluorescent, and LED lights as well as fans.

FEATURES

- 7 buttons preset timer switch
- For use with LED, incandescent, fluorescent lights, and fan motor
- Replace standard light or fan single pole switch
- Blue LED indicators - always ON
- Neutral Wire Required

SPECIFICATIONS

Voltage	120VAC, 60Hz
Resistive	6.4A
Tungsten	800W
Electronic Ballast	800VA
Motor	1/4 HP
Warranty	2 Years

TESTING & CODE COMPLIANCE



APPLICATIONS

- Closet
- Laundry Room
- Pantry
- Basement
- Garage
- Home Spa

SPECIFICATION SUBMITTAL

Job Name Job Number

Notes