## Enerices Toggle switch, lighted Residential grade



## MODEL NO: 88115L

## DESCRIPTION

The ENERLITES 88115L switch makes installation quick and simple with its versatile design. This switch features side mount wiring as well as push-in wiring on the rear (for use with copper wiring). The impact resistant thermoplastic body is built strong to endure years of use as well as being resistant to a wide temperature range. Toggle switch illuminates when load is off.

FEATURES	SPECIFICATIONS	
<ul> <li>Faster installation with combination of side wiring and push-in wiring</li> <li>Push-in terminals accept #14 solid wire only</li> <li>Easy-access green hex head ground screw</li> <li>Steel mounting strap, made of galvanized steel for corrosion resistance</li> <li>Removable yoke tabs for ideal alignment</li> <li>Large head combination screws for fast wiring</li> </ul>	Amperage Voltage Termination Actuator Material Operating Temperature Warranty	15 Amp 120VAC / 277VAC Rear Push In and Side Thermoplastic -104° F to 167° F 2 Years
TESTING & CODE COMPLIANCE	APPLICATIONS	
LISTED	<ul><li> Homes</li><li> Apartments</li><li> Condominiums</li></ul>	<ul><li> Offices</li><li> Hotels</li><li> Restaurants</li></ul>

## **SPECIFICATION SUBMITTAL**