

Enerlites®

WIFI SMART RECEPTACLE



MODEL NO: WF15RM

DESCRIPTION

The ENERLITES WF15RM is an in-wall WiFi smart receptacle with 15 Amp tamper-resistant duplex outlets. The top outlet is always ON and the bottom outlet's energy usage is monitored and reported by Smart Meter. Download the free Enerwave app to your mobile device and use it to control connected devices remotely, set scenes, create schedules, and more. The WF15RM can also be controlled through the Tuya Smart Life app, and connected devices are compatible with voice commands through Amazon Alexa or Google Assistant.

FEATURES

- Works with ENERWAVE Wi-Fi App, no hub required
- Compatible with Amazon Alexa/Google Home for voice control
- Requires in-wall installation with hard wired connections - neutral wire required
- Compatible with different loads including LED
- Save energy by automating ON/OFF times or using timer

SPECIFICATIONS

Amperage	15 Amp
Voltage	120VAC, 60Hz
Incandescent	1000W
Motor	1/2 HP
Ballast	1200 VA
Resistive	1800W
Signal Frequency	WiFi 2.4 Ghz

TESTING & CODE COMPLIANCE



APPLICATIONS

- Homes
- Apartments
- Condominiums
- Offices
- Hotels
- Restaurants

SPECIFICATION SUBMITTAL

Job Name

Job Number

Notes