

Enerlites®

Z-WAVE 15 AMP RECEPTACLE



MODEL NO: ZW15R-N

DESCRIPTION

The Z-Wave ZWN-15R-N is an in-wall smart receptacle with 15 Amp tamper-resistant duplex outlets. This receptacle requires a connection to a compatible Z-Wave hub to enable wireless controls (sold separately). The top outlet is always ON and the bottom outlet's energy usage is monitored and reported by Smart Meter. Connected devices are also compatible with voice commands through Amazon Alexa or Google Assistant.

FEATURES

- Alexa/Google Home voice control compatible - requires a Z-Wave Hub
- Increased energy efficiency with our Smart Meter Energy Monitoring technology
- Works with all certified Z-Wave devices (backwards compatible)
- Requires in-wall installation with hard-wired connections - neutral wire required
- Compatible with different loads
- Control many devices with a single controller locally, or via a computer/ mobile phone remotely
- Wireless range: up to 100 feet (30 meters)

SPECIFICATIONS

Amperage	15 Amp
Voltage	120VAC, 60Hz
Resistive	1800W
Signal Frequency	908.42 MHz
Incandescent	1000W
Ballast	1200 VA
Material	Thermoplastic

TESTING & CODE COMPLIANCE



APPLICATIONS

- Homes
- Apartments
- Condominiums
- Offices
- Hotels
- Restaurants

SPECIFICATION SUBMITTAL

Job Name Job Number
Notes