

Enerlites®

12-HOUR 7-BUTTON COUNTDOWN TIMER SWITCH

MODEL NO: HET06-12



DESCRIPTION

The ENERLITES HET06A-12 is an in-wall timer switch with 7 buttons. The buttons offer 6 preset countdown times ranging from 30 minutes to 12 hours and one manual ON/OFF button that can override the timer. The timer switch features blue LED indicators that stay ON for easy locating in the dark. This device can work with incandescent, fluorescent, and LED lights as well as fans.

FEATURES

- 7 buttons preset timer switch
- For use with LED, incandescent, fluorescent lights, and fan motor
- Replace standard light or fan single pole switch
- Blue LED indicators constantly ON when the switch is not in use
- Neutral wire required

SPECIFICATIONS

Voltage	120VAC, 60Hz
Resistive	15A
Tungsten	1000W
Standard Ballast	1200VA
Electronic Ballast/ LED	5A / 600W
Motor	1/2 HP
Warranty	2 Years

TESTING & CODE COMPLIANCE



APPLICATIONS

- Closet
- Laundry Room
- Pantry
- Basement
- Garage
- Home Spa

SPECIFICATION SUBMITTAL

Job Name

Job Number

Notes