

Enerlites®

2 HOUR 7-BUTTON COUNTDOWN TIMER SWITCH



MODEL NO: HET06-J-2H

DESCRIPTION

Wiring your lights or fan through a preset timer switch like the Enerlites HET06-J-2H can help save you money while adding a level of convenience and energy saving to your home. This Enerlites preset timer switch has the time adjustment from 5, 10, 20, 30 mins, 1, 2 hours. This unit works with LED, incandescent, fluorescent lamp and fan motor; ideal for closet, pantry, garage, laundry room, basement, outdoor lighting, and home spas.

FEATURES

- 7 buttons preset timer switch
- Replace standard light or fan single pole switch
- Blue LED indicator remain off when the switch is not in use
- Ground wire required

SPECIFICATIONS

Voltage	120VAC, 60Hz
Resistive	6.4A
Tungsten	800W
Electronic Ballast	800VA
Motor	1/4 HP
Warranty	2 Years

TESTING & CODE COMPLIANCE



APPLICATIONS

- Closet
- Pantry
- Garage
- Laundry Room
- Basement
- Home Spa

SPECIFICATION SUBMITTAL

Job Name		Job Number	
Notes			