

Enerlites®

60 MINUTES 7-BUTTON COUNTDOWN TIMER SWITCH

MODEL NO: HET06-J6



DESCRIPTION

Wiring your lights or fan through a preset timer switch like the Enerlites HET06-J6 can help save you money while adding a level of convenience and energy saving to your home. This Enerlites preset timer switch has the time adjustment from 1, 5, 10, 20, 30, and 60 minutes. This unit works with LED, incandescent, fluorescent lamp and fan motor; ideal for closet, pantry, garage, laundry room, basement, outdoor lighting, and home spas.

FEATURES

- 7 buttons preset timer switch
- For use with LED, incandescent, fluorescent lights, and fan motor
- Replace standard light or fan single pole switch
- Blue LED indicator remain off when the switch is not in use
- Ground wire required

SPECIFICATIONS

Voltage	120VAC, 60Hz
Resistive	6.4A
Tungsten	800W
Electronic Ballast	800VA
Motor	1/4 HP
Warranty	2 Years

TESTING & CODE COMPLIANCE



APPLICATIONS

- Closet
- Pantry
- Garage
- Laundry Room
- Basement
- Home Spa

SPECIFICATION SUBMITTAL

Job Name Job Number

Notes