

Enerlites®

4-HOUR 7-BUTTON COUNTDOWN TIMER SWITCH

MODEL NO: HET06-R



DESCRIPTION

The ENERLITES HET06-R is an in-wall timer switch with 7 buttons. The buttons offer 6 preset countdown times ranging from 5 minutes to 4 hours and one manual ON/OFF button that can override the timer. The timer switch features blue LED indicators with two different modes. In mode 1, the blue LED flashes twice to indicate success and then stays OFF. In mode 2, the blue LED stays ON during the selected time delay and then shuts OFF. This device can work with incandescent and fluorescent lights as well as fans.

FEATURES

- 7 buttons preset timer switch
- For use with LED, incandescent, fluorescent lights, and fan motor
- Sleek design mounts flush with wall plate
- Neutral wire required

SPECIFICATIONS

Voltage	120VAC, 60Hz
Resistive	15A
Tungsten	1000W
Electronic Ballast	1200 VA
Motor	1/2 HP
Warranty	2 Years

TESTING & CODE COMPLIANCE



APPLICATIONS

- Closet
- Laundry Room
- Pantry
- Basement
- Garage
- Home Spa

SPECIFICATION SUBMITTAL

Job Name

Job Number

Notes

