
Enerlites

MODEL 67500 50A Flush Mount Power Outlet




NEMA 10-50R 3 Wire, 3 Pole Rated at 50A 125/250 VAC, 60Hz

WARNING: Turn the POWER OFF at the circuit breaker before installing the receptacle.

Read and understand these instructions before installing. This device is intended for installation in accordance with the National Electric Code and local regulations. It is recommended that a qualified electrician performs this installation. Make sure to turn off the circuit breaker or fuse(s) and make sure power is off before wiring the device.

WARNING: DO NOT use with single-gang wall boxes, single-gang mud rings or single-gang box extenders.

NOTE: for use with #10 AWG thru #4 AWG copper, copper-clad or aluminum wire. Tighten terminal screws to 30 in-lbs of torque.



WIRING DIRECTIONS

- 1. Connect the RED/HOT wire to the Y terminal and tighten screw.
- 2. Connect the BLACK/HOT wire to the X terminal and tighten screw.
- 3. Connect the WHITE/NEUTRAL wire to the WHITE terminal and tighten screw.

WARRANTY INFORMATION

This device is warranted to be free of material and workmanship defects for 2 years from the date of purchase. Original receipt or proof of purchase from an authorized retailer must be presented upon warranty claim. ALL claims must be verified and approved by Enerlites, Inc. Warranties from other Enerlites products may vary. This warranty is nontransferable and does not cover normal wear and tear or any malfunction, failure, or defect resulting from misuse, abuse, neglect, alteration, modification, or improper installation. To the fullest extent permitted by the applicable state law, Enerlites shall not be liable to the purchaser or end user customer of Enerlites products for direct, incidental, or consequential damages even if Enerlites has been advised of the possibility of such damages. Enerlites total liability under this or any other warranty, express or implied, is limited to repair, replacement or refund. Repair, replacement or refund are the sole and exclusive remedies for breach of warranty or any other legal theory.

