

# TIMER FEATURES

## Astronomic Features

- Anti-theft feature
- Automatic ON/OFF based on programmed time
- Daylight savings time automatically updates



## Anti-Theft Feature

Settings to randomly turn your lights ON and OFF

## LED Light Indicators

Makes it easy to find in the dark



Enerlites Inc.  
www.enerlites.com



Toll Free: 1 877 372 6447  
Tell: 949 756 0536  
Fax: 949 756 0528  
sales@enerlites.com

# Enerlites®

Control. Charge. Connect.

## IN-WALL TIMERS



Browse our catalog!



©2023 Enerlites, Inc. All rights reserved.  
Enerlites is a trademark of Enerlites, Inc.  
Products, product images, and product specifications are subject to change. Enerlites is not responsible for inadvertent errors. All other trademarks or trade names used in this document are the property of their respective holders.

# Enerlites®

www.enerlites.com




**HET01-H1**



**HET01**




**HET06A-R**  
**HET06A-J**



**HET06-J6**  
**HET06-J-2H**



**HET06-R**  
**HET06-J**



**HET06-12**



**HMT01N**

<b>Description</b>	Single Pole/3-Way Astronomic Digital In-Wall Programmable Timer Switch	Single Pole 7-Day Digital In-Wall Programmable Timer Switch	Single Pole 30-Minute 7-Button Preset Countdown Timer Switches	Single Pole 60-Min/2-Hr 7-Button Preset Countdown Timer Switches	Single Pole 4-Hour 7-Button Preset Countdown Timer Switches	Single Pole 12-Hour 7-Button Preset Countdown Timer Switch	Single Pole 24-Hour Programmable Mechanical In-Wall Timer Switch
	Program for individual day, weekdays, and weekends	Program for individual day, weekdays, and weekends	HET06A-R 1-5-10-15-20-30 Minutes LED Always ON Neutral Wire Required	HET06-J6 1-5-10-20-30-60 Minutes Ground Wire Required	HET06-R 5-10-30-60 Minutes, 2-4 Hours Neutral Wire Required 2 Mode LED	30-Minute, 1-2-4-8-12 Hours LED Always ON  Neutral Wire Required	24 Hour ON/OFF  30 Minutes per pin  Neutral Wire Required
	Daylight savings (DST) Random mode (RND)	Daylight savings (DST) Random mode (RND)	HET06A-J 1-5-10-15-20-30 Minutes Ground Wire Required	HET06-J-2H 5-10-20-30-60-120 Minutes Ground Wire Required	HET06-J 5-10-30-60 Minutes, 2-4 Hours Ground Wire Required		
	Program lights to turn ON/OFF at dusk and dawn	Neutral Wire Required					
<b>Rating</b>	Voltage: 120VAC, 60Hz Resistive: 15A Tungsten: 1200W Standard Ballast: 1200VA Electronic Ballast: 5A (600W) Motor: 1/2HP	Voltage: 120VAC, 60Hz Resistive: 15A Tungsten: 1200W Standard Ballast: 1200VA Motor: 1/2HP	Voltage: 120VAC, 60Hz Resistive: 6.4A Tungsten: 800W Electronic Ballast: 800VA Motor: 1/4HP	Voltage: 120VAC, 60Hz Resistive: 6.4A Tungsten: 800W Electronic Ballast: 800VA Motor: 1/4HP	Voltage: 120VAC, 60Hz Resistive: HET06-R: 15A HET06-J: 6.4A  Tungsten: HET06-R: 1000W HET06-J: 800W  Electronic Ballast: HET06-R: 1200VA HET06-J: 800VA  Motor: HET06-R: 1/2HP HET06-J: 1/4HP	Voltage: 120VAC, 60Hz Resistive: 15A Tungsten: 1000W Standard Ballast: 1200VA Electronic Ballast: 5A (600W) Motor: 1/2HP	Voltage: 120VAC, 60Hz Resistive: 15A Tungsten: 1250W Electronic Ballast: 500VA Motor: 1/2HP
	White	White, Ivory	HET06A-R: White, Ivory HET06A-J: White	White	HET06-R: White, Ivory HET06-J: White	White	White
<b>Warranty</b>	2 years	2 years	2 years	2 years	2 years	2 years	2 years